SDEC Engine Brushless Alternator 350kVA Automatic Diesel Generator

Basic Information

Place of Origin: CHINA
Brand Name: DELLENT
Certification: CE/ISO9001
Model Number: DE-SC385
Minimum Order Quantity: 1*20GP
Price: face to face

Packaging Details: PLASTIC WRAP OR PLYWOOD CASE
 Delivery Time: 30 DAYS FROM DEPOSIT RECEIVED

Payment Terms: L/C, T/T

• Supply Ability: 500 PCS PER MONTH



Product Specification

Name: Automatic Diesel Generator

• Engine Model: 6ETAA11.8-G21

Frequency: 50HzEngine Brand: SDEC

• No. Of Cylinder: 6 Cylinder In Line

Rated Speed: 1500rpmVoltage: 400V/230VWarranty: 12 Months

Controller: Automatic Start/Stop
 Prime Power: 280kW/350kVA
 Standby Power: 308kW/385kVA

• Alternator Type: Brushless, Self-excitation

• Highlight: SDEC Engine Brushless Alternator,

350kVA Automatic Diesel Generator,

350kVA Diesel Generator

Brushless Alternator 350kVA Automatic Diesel Generator

. PRODUCT DESCRIPTION

350kva Standby Power SDEC Genset Soundproof Engine By 6 Cylinder In Line

Dellent Power supply the standby power 220kVA water cooled diesel generator with SDEC brand diesel engine model6ETAA11.8-G21. The water cooled diesel generator with rated output 350kVA /280kW, standby power385kVA / 308kW.



110kVA Diesel Generator Powered by SDEC Diesel Engine:

Model		DE-SC385	
Max. Power	kVA	385.0	
	kW	308.0	
Rate Power	kVA	350.0	
	kW	280.0	
Frequency	Hz	50	
Rate Voltage	V	380/220V	
Rate Current	A	531	
SDEC Diesel Engine:			

SDEC Diesei Eligilie.		
Engine Manufacturer	Shanghai Diesel Engine Co., Ltd.	
Engine Brand	SDEC	
Engine Model	6ETAA11.8-G21	
No. of Cylinder	6 Cylinder in line	
Aspiration	Turbocharged and Air to Air Aftercooled	
Governor	Electric	
Engine Max. Output Power	kW	338
Displacement	L	11.800
Starting Voltage	V	24
Bore	mm	128
Stroke	mm	153
Lubrication Oil Capacity	L	33-41
Compression Ratio	17 : 1	
Fuel Tank Capacity	L	450
Fuel Consumption at 100% Load	L/H	72.5

Specification of Control Panel:

Controller Brand		Deepsea		
Controller Model		DSE6120		
Breaker Brand		Delixi		
Breaker Capacity	A	630		
Battery Charger	Sm	Smartgen Model BAC06A		
Emergency Stop Button		Supply		
Automatic Mains Fail (AMF)		Supply		
Fuel Level		Supply		
Automatic Transfer Switch		ATS as optional part		

. Why Choose Us:

Dedicated

We are DEDICATED to meet Customers' need.

Enthusiasm

We respond to our Customers' ENTHUSIASM

Loyalty

We cherish our Customers' LOYALTY

Luxury

We aim to establish our own LUXURY brand

Efficient

We offer our EFFICIENT service

Newest

We adopt NEWEST technologies for products

Trust

We strive for winning the TRUST from Customers

. QUALIFICATION CENTIFICATE:



















. FACTORY INTERIOR:





Fuan Dellent Electric & Machinery Co., Ltd.







NO.7,JINYE ROADTIEHU INDUSTRIAL AREA CHENGYANG TOWN, FUAN CITY,NINGDECITY,FUJIAN.CHINA